

# Configurations

LR-5200-IR Advanced Intelligent DSP IR Receiver

## Architectural Specs

The IR receiver shall be capable of receiving on four (4) wide band channels (carriers), Channel 1 (2.3 MHz), Channel 2 (2.8 MHz), Channel 3 (3.3 MHz) and Channel 4 (3.8 MHz). The device shall have a programmable multi-function Listen button that can be tuned for the venues desired channels and electronically lock out any unused channels. The receiver shall have the option of being lanyard or belt clip worn and the lanyard shall incorporate an integrated neck loop for compatibility with T-coil hearing aids. The receiver shall be intelligent and provide customized audio to either earphones or the integrated neck loop based upon which is connected. The receiver shall have two (2) 3.5 mm (TRRS) connectors to drive the integrated neck loop lanyard or up to two (2) mono or stereo earphones. The receiver shall incorporate a multi-functional display (OLED) that indicates battery status, inventory number, volume level and a customizable channel name. The receiver shall employ a unique iDSP™ noise reduction technology. The receiver shall be fully programmable via PC software. The receiver shall have a micro USB connector used for programming/setup, inventory control, charging and firmware upgrades. The receiver shall incorporate automatic battery charging circuitry and use a non-proprietary lithium ion battery. The receiver shall automatically turn on when removed from the charging device and automatically turn off when returned to the charging device. The receiver shall have additional charging contacts to allow for multiply charging options. The receiver shall have a signal-to-noise ratio of 60 dB or greater, THD less than 2% and shall have an audio frequency response of 63 Hz – 15 kHz ( $\pm 3$  dB). The Listen LR-5200-IR is specified.